

LSG750/752

The **LSG750** is a CAN BUS foldable and programmable LED sign, with two levels of light intensity (day/night) and capacity for 200 totally programmable messages. In addition the **LSG750 2N** version includes 2 integrated NanoLEDs in vertical position with flash pattern and cruise light.

LSG752 model includes the same electronic features as the LSG750, but with a vertical mounting system.

The LSG750/752 sign range are controlled through the BCT3009, with LCD screen and selection buttons. It allows, through a simple menu system, to select and preview the message before it appears on the LED sign.

Through the SmartSign 2 Message Editor software, it is easy to edit and upload the 200 messages to the control head. It allows to program letters, numbers and symbols (arrows, square, etc.), and integrates scrolling and mirror effect message options. In addition, it has a wide library of the most usual messages in different countries.

Voltage:	12 V
Number of programmable messages:	200
Number of lines by message:	8
Number of characters in display:	10
Dimensions screen:	LSG 750: 440 x 65 mm LSG 750 2N: 440 x 65 mm LSG 752: 500 x 79 mm
Dimensions screen:	60 x 7 LEDs
LED colour:	Red
Day/night function:	LSG 750: Yes LSG 750 2N: No LSG 752: Yes
Current consumption:	4 A
Radiation angle:	+/- 15°
Dimensions sign:	LSG 750: 570 x 160 x 160 mm LSG 750 2N: 570 x 160 x 160 mm LSG 752: 538 x 103 x 17 mm
Weight:	LSG 750: 2800 gr LSG 750 2N: 2900 gr LSG 752: 705 gr



Sign LSG750



Sign LSG750 2N



Sign LSG752

REF.	MOD.	DESCRIPTION
2025583	LSG750	Programmable and foldable LED sign with day/night function. 200 Programmable messages by SmartSign 2 Message Editor, controlled through the BCT3009 control head with screen to display messages.
2025584	LSG750 2N	Programmable and foldable LED sign, with (2) blue NanoLED integrated (approved UN R65 Class 1). 200 Programmable messages by SmartSign 2 Message Editor, controlled through the BCT3009 control head with screen to display messages.
2025587	LSG752	Programmable and fixed mounting LED Sign with day/night function. 200 Programmable messages by SmartSign 2 Message Editor, controlled through the BCT3009 control head with screen to display messages.
BCT3009	BCT3009	Control head*
2025473	S2ME	SmartSign2 Message Editor, for editing and downloading SmartSign programmable LED Sign messages from PC.

*For other control head, please consult to our Commercial Department.